



Wiring Information	
Power	10AWG / 150°C / 600V
Control	16-22AWG / 105°C / 600V
Power Supply Wire Gauge assumes 75°C Copper Wire. See hotkilns.com/wire-size.	

Model: e18T-208-3P	
Voltage	208 / 3 / 50-60
Watts	8,400
Full Load Amps	L1 23.3 L2 23.3 L3 23.3
Power Supply	Fuse 30A Wire 10AWG
Elements	QTY OHMS
E-E-18TL/21	6 7.44

Model: e18T-240-3P	
Voltage	240 / 3 / 50-60
Watts	8,400
Full Load Amps	L1 20.2 L2 20.2 L3 20.2
Power Supply	Fuse 30A Wire 10AWG
Elements	QTY OHMS
E-E-18TL/31	6 9.90

Industrial & commercial applications may require the installation of a LOCKOUT/TAGOUT device to prevent the kiln from operating during maintenance.

This kiln is recommended to be wired & connected to an approved U. L. & NEC configured receptacle controlled with a disconnect switch and properly fused according to the KW load specification listed on the kiln nameplate. L&L Kiln Mfg., Inc., also recommends fuses rather than circuit breakers to prevent nuisance tripping.

E18T Easy-Fire 3 Phase 208V, 240V (C0014)				
A	05/12/2026		AF	Drawn by: AF
Rev.	Date	Description	Approved by	Dwg. No. C0014