



| Wiring Information | |
|---|-------------------------|
| Power | 10AWG / 150°C / 600V |
| Control | 16-22AWG / 105°C / 600V |
| Power Supply Wire Gauge assumes 75°C Copper Wire. See hotkilns.com/wire-size. | |

| Model: e28T-208 | | |
|--------------------------------|-----------------|-------|
| Voltage | 208 / 1 / 50-60 | |
| Watts | 9,985 | |
| Full Load Amps | L1 | L2 L3 |
| | 48.0 | 48.0 |
| Power Supply | Fuse | Wire |
| | 60A | 6AWG |
| Standard Elements: E-E-28TL/21 | | |
| Quad Elements: E-E-28TU/21 | | |
| Quantity: 6 | Ohms: 25.0 | |

| Model: e28T-240 | | |
|--------------------------------|-----------------|-------|
| Voltage | 240 / 1 / 50-60 | |
| Watts | 11,520 | |
| Full Load Amps | L1 | L2 L3 |
| | 48.0 | 48.0 |
| Power Supply | Fuse | Wire |
| | 60A | 6AWG |
| Standard Elements: E-E-28TL/31 | | |
| Quad Elements: E-E-28TU/31 | | |
| Quantity: 6 | Ohms: 28.9 | |

Industrial & commercial applications may require the installation of a LOCKOUT/TAGOUT device to prevent the kiln from operating during maintenance.

This kiln is recommended to be wired & connected to an approved U. L. & NEC configured receptacle controlled with a disconnect switch and properly fused according to the kW load specification listed on the kiln nameplate. L&L Kiln Mfg., Inc., also recommends fuses rather than circuit breakers to prevent nuisance tripping.

| E28T Easy-Fire 1 Phase 208V, 240V (C0036) | | | | |
|---|------------|-------------|-------------|----------------|
| | | | | |
| A | 05/06/2026 | | AF | Drawn by: AF |
| Rev. | Date | Description | Approved by | Dwg. No. C0036 |